SQ76003D3/SQ76003E3

High Efficiency, 3 A , 2.5V- 6V Input Synchronous Step Down DC/DC converter

General Description

The SQ76003D3 and SQ76003E3 are a step-down module converter with built-in power MOSFETs and inductor. The SQ76003D3 and SQ76003E3 can deliver up to 3A of continuous output current from a 2.5V to 6V input voltage with excellent load and line regulation. The output voltage can be configured as low as 0.6V using an external resistor divider. Only input capacitors, output capacitor and the resistor divider are needed to complete the design.

The device is available in a 2.5mm x 2 mm QFN package and operates over a temperature range of -40°C to 125°C.

Applications

- Smart Phones
- Telecom Applications
- Optical Modules
- General POL Applications

Features

- 2.5V to 6V Input Voltage Range
- 3A Continuous Output Current
- Quiescent Current 24μA (typ.)
- Accurate ±1% V_{REF} Voltage
- 2.4MHz Pseudo-constant switching frequency
- Internal Soft-Start Limits Inrush Current
- Power-Good Indicator
- 100% duty cycle operation
- PFM/FCCM under light load condition:
  - SQ76003D3AAE: FCCM
  - SQ76003E3AAE: PFM
- Reliable Protection Modes:
  - Auto-retry Mode for UVLO and OTP.
  - Hiccup Mode for OCP
- Compact Package: QFN2.5×2-10
  Height: 1.22mm max
  MSL-1 Compliant

Typical Application



Figure 1. Application Circuit



Figure 2. Efficiency vs. Output Current

© 2024 Silergy Corp. All Rights Reserved.

Ordering Information

Ordering Part Number	Operating Mode Under Light Load	Package Type
SQ76003D3AAE	FCCM	QFN2.5×2-10 RoHS-Compliant and Halogen-Free
SQ76003E3AAE	PFM	

Pinout (top view)



Pin No	Pin Name	Pin Description
1, 2	VIN	Input pin. Decouple this pin to GND pin with at least 20μF ceramic capacitor.
3	EN	Enable pin. Pull high to enable the device. Pull low to disable the device.
4	PG	Power good open drain output pin. Connect to GND or leave floating if not used.
5, 6, 7	VOUT	Output voltage pin. Decouple this pin to GND pin with at least a 30μF ceramic capacitor.
8	FB	Output Feedback Pin. Connect this pin to the center point of the output resistor divider to program the output voltage: $V_{OUT}=0.6\times(1+R_H/R_L)$.
9, 10	GND	Ground pin.

© 2024 Silergy Corp. All Rights Reserved.

Block Diagram



Figure 3. Block Diagram

Absolute Maximum Ratings

Parameter (Note 1)	Min	Max	Unit
VIN	-0.3	7	V
All Other Pins	-0.3	VIN + 0.3	
Junction Temperature, Operating	-40	125	°C
Lead Temperature (Soldering,10sec.)		260	
Storage Temperature	-55	125	

Note 1:

Dynamic VDS for HS and LS MOSFET Tested Down to -1V----------500ns
Dynamic VDS for HS and LS MOSFET Tested Down to -5V----------20ns
Dynamic VDS for HS and LS MOSFET Tested Up to +7.5V----------500ns
Dynamic VDS for HS and LS MOSFET Tested Up to +9V----------20ns

Thermal Information

Parameter (Note 2)	Typ	Unit
θ_{JA} Junction-to-Ambient Thermal Resistance	28	°C/W
Ψ_{JB} Junction-to-Board Thermal Resistance	20	
θ_{JC} Junction-to-Case Thermal Resistance	0.08	
P_D Power Dissipation T_A = 25°C	3.6	W

© 2024 Silergy Corp. All Rights Reserved.

Recommended Operating Conditions

Parameter (Note 3)	Min	Max	Unit
Input Voltage	2.5	6	V
Output Voltage	0.6	V_{IN}	V
Output Current	0	3	A

Electrical Characteristics

(V_{IN} = 3.3V, V_{OUT} =1.8V,C_{OUT} =3×10μF, T_J = -40°C to +125°C, typical values are at T_J = 25°C, unless otherwise specified (Note 4). The values are guaranteed by test, design or statistical correlation, FB divider resistor accuracy = 0.5%, unless otherwise specified)

Parameter		Symbol	Test Conditions	Min	Typ	Max	Unit
Input Specifications	Input Voltage Range	V_{IN}		2.5		6	V
	Input UVLO Threshold (falling)	$V_{UVLO,FALLING}$	EN=V_{IN}	2	2.2	2.3	
	UVLO, Hysteresis	V_{HYS}	V_{IN} falling		200		mV
	Input Current with No Load (SQ76003D3AAE)	I_{IN}	I_O=0A	10	16	30	mA
	Quiescent Current	I_Q	V_{FB}=105%×V_{REF}		24	50	μA
	Shutdown Current	I_{SHDN}			0.1	15	μA
Output Specifications	Feedback Reference Voltage	V_{VREF}		0.594	0.6	0.606	V
	Load Regulation(Note5)	ΔV_{LDR}	Io=0-3A			±1	%
	Line Regulation(Note5)	ΔV_{LNR}	V_{IN}=2.5-6V			±0.5	%
	Temperature Regulation(Note5)	ΔT_{TMR}	T_A=-40°C to 105°C			±2	%
	Bottom FET Valley Current Limit	$I_{LIM,BOT}$			5		A
	Rise Time	t_{RISE}	From EN high to 95% of V_{OUT} nominal	0	0.3	1	ms
General Specifications	Switching Frequency	f_{SW}		1.92	2.4	2.88	MHz
	Thermal Shutdown Temperature	T_{SD}			150		°C
	Thermal Shutdown Hysteresis	T_{HYS}			20		°C
	Maximum Duty Cycle (Note5)	D_{MAX}		100			%
	Min On Time(Note5)	$t_{ON,MIN}$			50		ns
Signal Specifications	EN Pin Logic High Threshold (rising)	$V_{EN,H}$		1.0			V
	EN Pin Logic Low Threshold (falling)	$V_{EN,L}$				0.4	V
	EN Pull-down Resistance	R_{EN}	V_{IN}=3.3V, EN=0.5V	300	400	500	kΩ
	Power Good Asserts Threshold	$V_{PG,ASSERTS}$	V_{OUT} rising	92	95	98	%
			V_{OUT} falling	85	88	91	%

© 2024 Silergy Corp. All Rights Reserved.

Note 1: Stresses beyond the “Absolute Maximum Ratings” may cause permanent damage to the device. These are stress ratings only. Functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

Note 2: θ_{JA} and Ψ_{JB} are based on a four-layer Silergy Evaluation Board (1.6mm thickness, 2OZ copper, 95% copper coverage) in the natural convection at T_A = 25°C. Junction temperature (T_J) refers to the hottest device, which is inductor temperature and case temperature (T_C) as well for this product. Board temperature (T_B) refers to the PCB point to the hottest IC pin with a 1mm distance on the same PCB surface layer.

Note 3: The device is not guaranteed to function outside its operating conditions.

Note 4: Production testing is performed at 25˚C; limits at -40°C to +125°C are guaranteed by design, test or statistical correlation. The Module operating temperature range : -40°C to +105°C;The Die operating temperature range : -40℃ to +125°C;The Inductor operating temperature range : -40°C to +115°C.

Note 5: The values are guaranteed by design, not production testing.

© 2024 Silergy Corp. All Rights Reserved.

Typical Performance Characteristics

(C_{OUT} = 3×10μF, T_A = 25°C, resistor tolerance is ±1%, unless otherwise specified)

SQ76003D3AAE

V_{OUT}=0.75V

Efficiency vs Output Current



Load Transient

(V_{IN}=3.3V, V_{OUT}=0.75V, I_{OUT}=0.3~3A)



Time (200μs/div)

Output Ripple

(V_{IN}=3.3V, V_{OUT}=0.75V, I_{OUT}=3A)



Time (400ns/div)

Output Ripple

(V_{IN}=3.3V, V_{OUT}=0.75V, I_{OUT}=0A)



Time (400ns/div)

Startup from EN

(V_{IN}=3.3V, V_{OUT}=0.75V, I_{OUT}=3A)



Time (200μs/div)

Shutdown from EN

(V_{IN}=3.3V, V_{OUT}=0.75V, I_{OUT}=3A)



Time (200μs/div)

© 2024 Silergy Corp. All Rights Reserved.

Startup from V_{IN}

(V_{IN}=3.3V, V_{OUT}=0.75V, I_{OUT}=3A)



Time (2ms/div)

Shutdown from V_{IN}

(V_{IN}=3.3V, V_{OUT}=0.75V, I_{OUT}=3A)



Time (2ms/div)

Short Circuit Protection

(V_{IN}=3.3V, V_{OUT}=0.75V, I_{OUT}=0A-Short)



Time (10ms/div)

Short Circuit Protection

(V_{IN}=3.3V, V_{OUT}=0.75V, I_{OUT}=3A-Short)



Time (10ms/div)

V_{OUT}=1V

Efficiency vs Output Current



Load Transient

(V_{IN}=3.3V, V_{OUT}=1V, I_{OUT}=0.3A~3A)



Time (200μs/div)

© 2024 Silergy Corp. All Rights Reserved.

Output Ripple

(V_{IN}=3.3V, V_{OUT}=1V, I_{OUT}=3A)



Time (400ns/div)

Output Ripple

(V_{IN}=3.3V, V_{OUT}=1V, I_{OUT}=0A)



Time (400ns/div)

Startup from EN

(V_{IN}=3.3V, V_{OUT}=1V, I_{OUT}=3A)



Time (200μs/div)

Shutdown from EN

(V_{IN}=3.3V, V_{OUT}=1V, I_{OUT}=3A)



Time (200μs/div)

Startup from V_{IN}

(V_{IN}=3.3V, V_{OUT}=1V, I_{OUT}=3A)



Time (2ms/div)

Shutdown from V_{IN}

(V_{IN}=3.3V, V_{OUT}=1V, I_{OUT}=3A)



Time (2ms/div)

© 2024 Silergy Corp. All Rights Reserved.

Short Circuit Protection

(V_{IN}=3.3V, V_{OUT}=1V, I_{OUT}=0A-Short)



Time (10ms/div)

Short Circuit Protection

(V_{IN}=3.3V, V_{OUT}=1V, I_{OUT}=3A-Short)



Time (10ms/div)

V_{OUT}=1.2V

Efficiency vs Output Current



Load Transient

(V_{IN}=3.3V, V_{OUT}=1.2V, I_{OUT}=0.3~3A)



Time (200μs/div)

Output Ripple

(V_{IN}=3.3V, V_{OUT}=1.2V, I_{OUT}=3A)



Time (400ns/div)

Output Ripple

(V_{IN}=3.3V, V_{OUT}=1.2V, I_{OUT}=0A)



Time (400ns/div)

© 2024 Silergy Corp. All Rights Reserved.

Startup from EN

(V_{IN}=3.3V, V_{OUT}=1.2V, I_{OUT}=3A)



Time (200μs/div)

Shutdown from EN

(V_{IN}=3.3V, V_{OUT}=1.2V, I_{OUT}=3A)



Time (200μs/div)

Startup from V_{IN}

(V_{IN}=3.3V, V_{OUT}=1.2V, I_{OUT}=3A)



Time (2ms/div)

Shutdown from V_{IN}

(V_{IN}=3.3V, V_{OUT}=1.2V, I_{OUT}=3A)



Time (2ms/div)

Short Circuit Protection

(V_{IN}=3.3V, V_{OUT}=1.2V, I_{OUT}=0A-Short)



Time (10ms/div)

Short Circuit Protection

(V_{IN}=3.3V, V_{OUT}=1.2V, I_{OUT}=3A-Short)



Time (10ms/div)

© 2024 Silergy Corp. All Rights Reserved.

V_{OUT}=1.8V

Efficiency vs Output Current



Load Transient

(V_{IN}=3.3V, V_{OUT}=1.8V, I_{OUT}=0.3~3A)



Time (200μs/div)

Output Ripple

(V_{IN}=3.3V, V_{OUT}=1.8V, I_{OUT}=3A)



Time (400ns/div)

Output Ripple

(V_{IN}=3.3V, V_{OUT}=1.8V, I_{OUT}=0A)



Time (400ns/div)

Startup from EN

(V_{IN}=3.3V, V_{OUT}=1.8V, I_{OUT}=3A)



Time (200μs/div)

Shutdown from EN

(V_{IN}=3.3V, V_{OUT}=1.8V, I_{OUT}=3A)



Time (200μs/div)

© 2024 Silergy Corp. All Rights Reserved.

Startup from V_{IN}

(V_{IN}=3.3V, V_{OUT}=1.8V, I_{OUT}=3A)



Time (2ms/div)

Shutdown from V_{IN}

(V_{IN}=3.3V, V_{OUT}=1.8V, I_{OUT}=3A)



Time (2ms/div)

Short Circuit Protection

(V_{IN}=3.3V, V_{OUT}=1.8V, I_{OUT}=0A-Short)



Time (10ms/div)

Short Circuit Protection

(V_{IN}=3.3V, V_{OUT}=1.8V, I_{OUT}=3A-Short)



Time (10ms/div)

Thermal Derating Curve @V_{IN}=3.3V



1) T_A: Air temperature, 0.5 inch above IC.
2) Based on a four-layer Silergy Evaluation Board in the natural convection.
3) The inductor temperature is not beyond 115℃ under this TD curve.
4) For customer's specific application, the recommended inductor temperature limitation is 115℃.

© 2024 Silergy Corp. All Rights Reserved.

SQ76003E3AAE

V_{OUT}=0.6V

Efficiency vs. Output Current



Load Transient

(V_{IN}=3.3V, V_{OUT}=0.6V, I_{OUT}=0.3~3A)



Time (200μs/div)

Output Ripple

(V_{IN}=3.3V, V_{OUT}=0.6V, I_{OUT}=3A)



Time (800ns/div)

Output Ripple

(V_{IN}=3.3V, V_{OUT}=0.6V, I_{OUT}=0A)



Time (100ms/div)

Startup from EN

(V_{IN}=3.3V, V_{OUT}=0.6V, I_{OUT}=3A)



Time (200μs/div)

Shutdown from EN

(V_{IN}=3.3V, V_{OUT}=0.6V, I_{OUT}=3A)



Time (200μs/div)

© 2024 Silergy Corp. All Rights Reserved.

Startup from V_{IN}

(V_{IN}=3.3V, V_{OUT}=0.6V, I_{OUT}=3A)



Time (2ms/div)

Shutdown from V_{IN}

(V_{IN}=3.3V, V_{OUT}=0.6V, I_{OUT}=3A)



Time (2ms/div)

Short Circuit Protection

(V_{IN}=3.3V, V_{OUT}=0.6V, I_{OUT}=0A-Short)



Time (10ms/div)

Short Circuit Protection

(V_{IN}=3.3V, V_{OUT}=0.6V, I_{OUT}=3A-Short)



Time (10ms/div)

V_{OUT}=1.2V

Efficiency vs. Output Current



Load Transient

(V_{IN}=3.3V, V_{OUT}=1.2V, I_{OUT}=0.3~3A)



Time (200μs/div)

© 2024 Silergy Corp. All Rights Reserved.

Output Ripple

(V_{IN}=3.3V, V_{OUT}=1.2V, I_{OUT}=3A)



Time (800ns/div)

Output Ripple

(V_{IN}=3.3V, V_{OUT}=1.2V, I_{OUT}=0A)



Time (20ms/div)

Startup from EN

(V_{IN}=3.3V, V_{OUT}=1.2V, I_{OUT}=3A)



Time (200μs/div)

Shutdown from EN

(V_{IN}=3.3V, V_{OUT}=1.2V, I_{OUT}=3A)



Time (200μs/div)

Startup from V_{IN}

(V_{IN}=3.3V, V_{OUT}=1.2V, I_{OUT}=3A)



Time (2ms/div)

Shutdown from V_{IN}

(V_{IN}=3.3V, V_{OUT}=1.2V, I_{OUT}=3A)



Time (2ms/div)

© 2024 Silergy Corp. All Rights Reserved.

Short Circuit Protection

(V_{IN}=3.3V, V_{OUT}=1.2V, I_{OUT}=0A-Short)



Time (10ms/div)

Short Circuit Protection

(V_{IN}=3.3V, V_{OUT}=1.2V, I_{OUT}=3A-Short)



Time (10ms/div)

V_{OUT}=1.8V

Efficiency vs. Output Current



Load Transient

(V_{IN}=3.3V, V_{OUT}=1.8V, I_{OUT}=0.3~3A)



Time (200μs/div)

Output Ripple

(V_{IN}=3.3V, V_{OUT}=1.8V, I_{OUT}=3A)



Time (800ns/div)

Output Ripple

(V_{IN}=3.3V, V_{OUT}=1.8V, I_{OUT}=0A)



Time (10ms/div)

© 2024 Silergy Corp. All Rights Reserved.

Startup from EN
(V_{IN}=3.3V, V_{OUT}=1.8V, I_{OUT}=3A)



Time (200μs/div)

Shutdown from EN
(V_{IN}=3.3V, V_{OUT}=1.8V, I_{OUT}=3A)



Time (200μs/div)

Startup from V_{IN}
(V_{IN}=3.3V, V_{OUT}=1.8V, I_{OUT}=3A)



Time (2ms/div)

Shutdown from V_{IN}
(V_{IN}=3.3V, V_{OUT}=1.8V, I_{OUT}=3A)



Time (2ms/div)

Short Circuit Protection
(V_{IN}=3.3V, V_{OUT}=1.8V, I_{OUT}=0A-Short)



Time (10ms/div)

Short Circuit Protection
(V_{IN}=3.3V, V_{OUT}=1.8V, I_{OUT}=3A-Short)



Time (10ms/div)

© 2024 Silergy Corp. All Rights Reserved.

V_{OUT}=3.3V

Efficiency vs. Output Current



Load Transient

(V_{IN}=5V, V_{OUT}=3.3V, I_{OUT}=0.3~3A)



Time (200μs/div)

Output Ripple

(V_{IN}=5V, V_{OUT}=3.3V, I_{OUT}=3A)



Time (800ns/div)

Output Ripple

(V_{IN}=5V, V_{OUT}=3.3V, I_{OUT}=0A)



Time (10ms/div)

Startup from EN

(V_{IN}=5V, V_{OUT}=3.3V, I_{OUT}=3A)



Time (200μs/div)

Shutdown from EN

(V_{IN}=5V, V_{OUT}=3.3V, I_{OUT}=3A)



Time (200μs/div)

© 2024 Silergy Corp. All Rights Reserved.

Startup from V_{IN}

(V_{IN}=5V, V_{OUT}=3.3V, I_{OUT}=3A)



Time (2ms/div)

Shutdown from V_{IN}

(V_{IN}=5V, V_{OUT}=3.3V, I_{OUT}=3A)



Time (2ms/div)

Short Circuit Protection

(V_{IN}=5V, V_{OUT}=3.3V, I_{OUT}=0A-Short)



Time (10ms/div)

Short Circuit Protection

(V_{IN}=5V, V_{OUT}=3.3V, I_{OUT}=3A-Short)



Time (10ms/div)

Thermal Derating Curve @V_{IN}=3.3V



1) T_A: Air temperature, 0.5 inch above IC.
2) Based on a four-layer Silergy Evaluation Board in the natural convection.
3) The inductor temperature is not beyond 115℃ under this TD curve.
4) For customer's specific application, the recommended inductor temperature limitation is 115℃.

© 2024 Silergy Corp. All Rights Reserved.

Applications Information

The following paragraphs provide guidance on selecting the input capacitor C_{IN}, the output capacitor C_{OUT}, and the feedback resistors (R_H and R_L) to meet the targeted application specifications.

Feedback Resistor Dividers R_H and R_L

Choose R_H and R_L to program the proper output voltage. To minimize the power consumption under light loads, it is desirable to choose large resistance values for both R_H and R_L. A value of between 10kΩ and 1MΩ is highly recommended for both resistors. If R_H =100kΩ is chosen, then R_L can be calculated to be:

$$R_L = \frac{0.6 \times R_H}{V_{OUT} - 0.6}$$

Input Capacitor C_{IN}

Consider the RMS current rating of the input capacitor, paralleling additional capacitors if required, to meet the calculated RMS ripple current,

$$I_{CIN_RMS} = I_{OUT} \times \sqrt{D(1-D)}$$

The worst-case condition occurs at D = 0.5, then

$$I_{CIN_RMSMAX} = \frac{I_{OUT}}{2}$$

For simplification, choose an input capacitor with an RMS current rating greater than half of the maximum load current.
The input capacitor value determines the input voltage ripple of the converter. If there is an input voltage ripple requirement for the system, choose an appropriate input capacitor that meets the specification.

Given the very low ESR and ESL of ceramic capacitors, the input
voltage ripple can be estimated by

$$V_{CIN_RIPPLECAP} = \frac{I_{OUT}}{f_{SW} \times C_{IN}} \times D \times (1-D)$$

The worst-case condition occurs at D = 0.5, then

$$V_{CIN_RIPPLECAP,MAX} = \frac{I_{OUT}}{4 \times f_{SW} \times C_{IN}}$$

Two typical X7R or better grade ceramic capacitors with higher than 10V rating and greater than 10μF capacitance are recommended for most applications. Place the capacitors really close to the VIN and GND pins, while minimizing the loop area formed by C_{IN}, and VIN/GND pins. An additional 100 nF capacitor used to reduce high frequency noise is recommended to be used in parallel and placed closest to the VIN/GND pins.

Obtaining a good input ripple performance is dependent on selecting capacitors that can handle the RMS ripple current.

Output Capacitor C_{OUT}

The output capacitor is selected to handle the output ripple requirements. Both steady state ripple and transient requirements must be taken into consideration when selecting this capacitor. For the best performance, it is recommended to use X7R or better grade ceramic capacitor with higher than 6.3V rating and greater than 30μF capacitance. Place this ceramic capacitor close to the VOUT and GND pins while minimizing the loop area.

If the output capacitance is larger than 100μF or other type of capacitor (polymer, tantalum…) is used, please contact Silergy supporting team to get more assessment.

$$V_{RIPPLE,ESR} = \Delta I_L \times ESR$$

$$V_{RIPPLE,CAP} = \frac{\Delta I_L}{8 \times C_{OUT} \times f_{sw}}$$

External Capacitor Recommendation

	Description	Vendor	PN
C_{IN}	10μF/10V/X7R,0603	Murata	GRM188D71A106KA73#
C_{OUT}	10μF/6.3V/X7T,0603	Murata	GRM188D70J106MA73D

PFM Mode

The SQ76003E3 uses PFM (Pulse Frequency Modulation) mode during light load operation, which can maintain the high efficiency by reducing the switching frequency.
While in PFM mode, the SQ76003E3 starts a new switching cycle when the output voltage falls below the target. Between switching cycles, the device enters a sleep state where most of the internal circuits will be turned off to reduce quiescent current. This control method enables improved efficiency for light load operation.

FCCM Mode

The SQ76003D3 operates in FCCM (Forced Continuous Inductor Current Mode). The low-side synchronous rectifier remains on until the next t_{ON} cycle, allowing continuous current flow through the inductor. This allows the device to maintain a relatively constant switching frequency over the output current range at the expense of reduced efficiency during light load operation.

Power Good Indicator

The power good indicator is an open drain output controlled by a window comparator connected to the

© 2024 Silergy Corp. All Rights Reserved.

feedback signal. If V_{FB} is greater than V_{PG} low threshold and less than V_{PG} high threshold for at least the power good delay time (low to high), PG will be high-impedance. Otherwise, it is pulled low. PG allowable current should not exceed 10mA. Ensure that a proper resistor value with a value between 10kΩ~100kΩ is used. The pull-up resistor can be connected to any active voltage rail that ensures a proper voltage level for the device this pin is connected to.

Over Current Protection

When the load current is increasing, as soon as the high side power MOSFET current gets higher than peak current limit threshold(~6A), the high side power MOSFET will turn off and the low side power MOSFET will turn on and stay on until the current going through it decreases below the valley current limit threshold(~5A). If the load current continues to increase, the output voltage will drop. When the output voltage drops to below 20% of the target the output, the Under Voltage Protection (UVP) is triggered and the device stops switching for a period of 1ms (typ.). A soft-start is initiated after the hiccup time and the device will attempt to restart. Normal operation is resumed if the overcurrent condition is removed.

The UVP fault detection is disabled during the startup sequence and one ms afterwards, as well as during shutdown.

Thermal Shutdown Protection

If the internal (die) temperature of SQ76003D3/E goes higher than the thermal shutdown temperature threshold (typical 150℃), the device turns off both MOSFETs and enters thermal shutdown protection mode. The device resumes operation when the temperature decreases below 130℃.

© 2024 Silergy Corp. All Rights Reserved.

Application Schematic (V_{OUT} = 1.8V)



BOM List

Designator	Description	Part Number	Manufacturer
C1	47μF/25V Electrolytic Cap		
C2,C3	10uF/10V/X7R,0603	GRM188D71A106KA73#	murata
C4,C5,C6	10uF/6.3V/X7T,0603	GRM188D70J106MA73D	murata
C7	120pF/100V/C0G,0603	GCM1885C2A121JA16#	murata
R1 ,R3	100kΩ,1%,0603		
R2	50kΩ,1%,0603(V_{OUT}=1.8V)		
R4	1MΩ,1%,0603		
R5	0Ω,1%,0603		

© 2024 Silergy Corp. All Rights Reserved.

Layout Design

To achieve a higher efficiency and better noise immunity, the C_{IN} and C_{OUT} be placed close to the device.

- C_{IN} must be close to the pins VIN and GND. The loop area formed by C_{IN} and GND must be minimized.
- C_{OUT} must be close to the pins VOUT and GND. The loop area formed by C_{OUT} and GND must be minimized.
- Place the FB components (R_H, R_L) as close to the FB pin as possible.
- It is desirable to maximize the PCB copper area connecting to the GND pin to achieve the best thermal and noise performance. If the board space allows, a large copper pour as shown below is highly recommended.



Figure 18. Suggested PCB Layout

© 2024 Silergy Corp. All Rights Reserved.

MQFN2.5X2-10 Package Outline Drawing



Top View



Bottom View



Side View



Recommended PCB layout
(Reference only)

Notes: 1.All dimension in millimeter and exclude mold flash & metal burr.

2.Center line on drawing refers to the chip body center.

© 2024 Silergy Corp. All Rights Reserved.

Taping & Reel Specification

1. Taping Orientation

MDFN2.5x2-10



Feeding Direction ⟶

2. Carrier Tape & Reel specification for packages



Package types	Tape width (mm)	Pocket pitch(mm)	Reel size (Inch)	Trailer * length(mm)	Leader * length (mm)	Qty per reel (pcs)
MDFN2.5x2-10	8	4	7"	400	160	2500

© 2024 Silergy Corp. All Rights Reserved.

Packaging Information

Device Code:

SQ76003D3AAE **KNX**

SQ76003E3AAE **KNT**

Label Information

W/O: XXXXXXXXXX

P/N: SQ76003D3AAE

QTY: XXXX

D/C Lot: XXXXXXXXXX

MSL3

Pb-Free

RoHS Compliant
Halogen Free

(The barcode is for demonstration only.)

W/O: XXXXXXXXXX

P/N: SQ76003E3AAE

QTY: XXXX

D/C Lot: XXXXXXXXXX

MSL3

Pb-Free

RoHS Compliant
Halogen Free

(The barcode is for demonstration only.)

© 2024 Silergy Corp. All Rights Reserved.

Revision History

The revision history provided is for informational purposes only and is believed to be accurate, however, not warranted. Please make sure that you have the latest revision.

Date	Revision	Change
Nov.21, 2023	Revision 0.9	Initial Release
Nov.21, 2023	Revision 1.0	Production Release

© 2024 Silergy Corp. All Rights Reserved.

IMPORTANT NOTICE

1. **Right to make changes.** Silergy and its subsidiaries (hereafter Silergy) reserve the right to change any information published in this document, including but not limited to circuitry, specification and/or product design, manufacturing or descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products are sold subject to Silergy's standard terms and conditions of sale.

2. Applications. Application examples that are described herein for any of these products are for illustrative purposes only. Silergy makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification. Buyers are responsible for the design and operation of their applications and products using Silergy products. Silergy or its subsidiaries assume no liability for any application assistance or designs of customer products. It is customer's sole responsibility to determine whether the Silergy product is suitable and fit for the customer's applications and products planned. To minimize the risks associated with customer's products and applications, customer should provide adequate design and operating safeguards. Customer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Silergy assumes no liability related to any default, damage, costs or problem in the customer's applications or products, or the application or use by customer's third-party buyers. Customer will fully indemnify Silergy, its subsidiaries, and their representatives against any damages arising out of the use of any Silergy components in safety-critical applications. It is also buyers' sole responsibility to warrant and guarantee that any intellectual property rights of a third party are not infringed upon when integrating Silergy products into any application. Silergy assumes no responsibility for any said applications or for any use of any circuitry other than circuitry entirely embodied in a Silergy product.

3. **Limited warranty and liability.** Information furnished by Silergy in this document is believed to be accurate and reliable. However, Silergy makes no representation or warranty, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. In no event shall Silergy be liable for any indirect, incidental, punitive, special or consequential damages, including but not limited to lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges, whether or not such damages are based on tort or negligence, warranty, breach of contract or any other legal theory. Notwithstanding any damages that customer might incur for any reason whatsoever, Silergy' aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Standard Terms and Conditions of Sale of Silergy.

4. **Suitability for use.** Customer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of Silergy components in its applications, notwithstanding any applications-related information or support that may be provided by Silergy. Silergy products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of an Silergy product can reasonably be expected to result in personal injury, death or severe property or environmental damage. Silergy assumes no liability for inclusion and/or use of Silergy products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

5. **Terms and conditions of commercial sale**. Silergy products are sold subject to the standard terms and conditions of commercial sale, as published at http://www.silergy.com/stdterms, unless otherwise agreed in a valid written individual agreement specifically agreed to in writing by an authorized officer of Silergy. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. Silergy hereby expressly objects to and denies the application of any customer's general terms and conditions with regard to the purchase of Silergy products by the customer.

6. **No offer to sell or license**. Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights. Silergy makes no representation or warranty that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right. Information published by Silergy regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from Silergy under the patents or other intellectual property of Silergy.

For more information, please visit: www.silergy.com

©2024 Silergy Corp. **All Rights Reserved.**

© 2024 Silergy Corp. All Rights Reserved.